

Configuration du 802.1X

Configuration du RADIUS

```
ProCurve Switch 2650(config)# radius-server host 192.168.1.50
ProCurve Switch 2650(config)# aaa authentication port-access eap-radius
```

Activation sur des ports

```
ProCurve Switch 2650(config)# aaa port-access authenticator 15
LACP has been disabled on 802.1x port(s).
```

Bascule de VLAN en cas d'échec d'authentification

```
ProCurve Switch 2650(config)# aaa port-access authenticator 15 unauth-vid 200
ProCurve Switch 2650(config)# aaa port-access authenticator 15 client-limit 5
```

Activation

```
ProCurve Switch 2650(config)# aaa port-access authenticator active
```

Vérification

```
ProCurve Switch 2650(config)# show port-access authenticator

Port Access Authenticator Status

Port-access authenticator activated [No] : Yes
Allow RADIUS-assigned dynamic (GVRP) VLANs [No] : No

Current Current Cntrl
Port Status VLAN ID Port COS Dir
-----
15 Closed 1 No-override both
```

