

Routeur Cisco

- [Mettre à jour l'IOS \(ISR\) en USB](#)
- [Supprimer la configuration](#)
- [Ajouter une configuration en USB](#)


```
[R0]:  
/bootflash/isr4300-universalk9.16.06.06.SPA  
  
Do you want to remove the above files? [y/n]n  
[R0]:  
  
SUCCESS: install_remove Fri Jul 5 07:37:38 UTC 2024  
  
Router#
```

Etape 6 : Booter sur le nouveau IOS

```
Router(config)#boot system flash:isr4300-universalk9.16.06.06.SPA.bin  
Router(config)#wr
```

Etape 7 : Reboot

```
Router#reload  
Proceed with reload? [confirm]
```

Etape 8 : Vérification de la version

```
Router#sh ver  
Cisco IOS XE Software, Version 17.09.03a  
Cisco IOS Software [Cupertino], ISR Software (X86_64_LINUX_IOSD-UNIVERSALK9-M), Version  
17.9.3a, RELEASE SOFTWARE (fc2)  
Technical Support: http://www.cisco.com/techsupport  
Copyright (c) 1986-2023 by Cisco Systems, Inc.
```

Bonus : Supprimer le vieux IOS :

```
Router#delete flash:c1100-universalk9.17.03.04a.SPA.bin  
Delete filename [c1100-universalk9.17.03.04a.SPA.bin]?  
Delete bootflash:/c1100-universalk9.17.03.04a.SPA.bin? [confirm]  
Router#
```

Supprimer la configuration

Supprimer la configuration

```
router#erase startup-config
*****
*****
Erasing Nvram will not clear license trust code.
*****
*****
Erasing the nvram filesystem will remove all configuration files! Continue? [confirm]
[OK]
Erase of nvram: complete
router#
router#reload
WARNING:
Boot variable either does not exist or buffer is too small
This may impact autoboot of the router. Proceed with caution
Do you wish to proceed with reload anyway[confirm]
Proceed with reload? [confirm]
*Oct 20 12:49:11.992 UTC: %IOSXE_RP_CFG_NOT-3-BOOT_VAR_NOT_SET: Either the boot variable does
not exist or the buffer is too small.Keep it blank.
[confirm]
*Oct 20 12:49:15.326 UTC: %SYS-5-RELOAD: Reload requested by cisco on console. Reload Reason:
Reload Command.
```

Ajouter une configuration en USB

```
Router#enable
Router#dir usb0:
Directory of usb0:/

 5      -rwx           9953   Nov 5 2025 10:22:00 +00:00  conf.txt
 4      -rwx          685683088 Nov 5 2025 08:40:30 +00:00  c1100-
universalk9.17.09.03a.SPA.bin
 3      drwx           8192   Aug 22 2025 11:37:32 +00:00  System Volume Information

15565045760 bytes total (14879309824 bytes free)
Router#
Router#
Router#copy usb0: startup-config
Source filename []? conf.txt
Destination filename [startup-config]?
9953 bytes copied in 3.208 secs (3103 bytes/sec)
Router#
Router#reload
WARNING:
Boot variable either does not exist or buffer is too small
This may impact autoboot of the router. Proceed with caution
Do you wish to proceed with reload anyway[confirm]
Proceed with reload? [confirm]
```