

# Configuration de Port-security

## Configuration de port-security

```
ProCurve Switch 2650(config)# port-security ethernet 48 learn-mode
continuous      Continuous MAC address learn mode.
static          Static MAC address learn mode.
configured      Static MAC address configured mode.
port-access     Learn port-access authorized MAC address only.
limited-continuous Limited continuous MAC address learn mode.
```

## Limite d'adresse MAC

```
ProCurve Switch 2650(config)# port-security ethernet 48 address-limit <NB Adresses MAX>
```

## Alarme

```
ProCurve Switch 2650(config)# port-security ethernet 48 action
none
send-alarm
send-disable
```

## Fixer une adresse MAC

```
ProCurve Switch 2650(config)# port-security ethernet 48 mac-address 00:00:00:00:00:01
```

## Expiration de l'adresse MAC avant nouvelle apprentissage

```
ProCurve Switch 2650(config)# mac-age-time 60
```

## Vérification

```
ProCurve Switch 2650(config)# show port-security ethernet 48
```

## Port Security

Port : 48

Learn Mode [Continuous] : Continuous

Action [None] : None

---

## Revision #1

Created 11 March 2024 17:29:30 by Dunnload

Updated 11 March 2024 17:29:44 by Dunnload